



#### **Bachelor Thesis Presentation**

# Development and Implementation of an Automated Measurement System for RF Parameters of a DECT System

Alireza Ghaffari

University of Duisburg-Essen Prof. Dr. -Ing. Klaus Solbach


Lantiq Deutschland GmbH

# **Outline**

- Task Description
- Introduction to DECT
- Remote Controlling Measurement Equipment
- Automation of DECT Measurements
- Conclusion

# Task Description


- Developing an automated measurement system to test RF parameters of a DECT system
- Measurements according to ETSI EN 301 406
- Test cases as an extension to Lantiq's software Coreco written in TCL/TK
- Performing the measurements for a DECT system




# Introduction

#### **DECT**

- A standard for Cordless telephone systems
- 1880 MHz to 1900 MHz
- FDMA: 10 channels
- TDMA: 24 time slots
- Modulation scheme:
  GFSK with Δf = ± 288 kHz






# Introduction

#### **Packet Structure**

- Data is transmitted within slots in physical packets
- Bit p0: beginning of the packet



# Remote Controlling Measurement Equipment


- Measurement Equipment:
  - General: PC, temperature chamber, power supply
  - Tx tests: Spectrum analyzer
  - Rx tests: signal generator, function generator
- Connection via GPIB or RS-232

sp fsp FM DEMOD SETTINGS

Offset Samples: manual

- Define SCPI command and corresponding button for each instrument function
- Use Coreco record function to build test cases

Trigger Source: EXT - Trigger Slope: POS -



fsp\_demod\_commands ---

SELECT MODE

Demod Settings

FM Demod Settings

":SENS:ADEM:SET \$sample\_rate,\$record\_length,\$trigger\_source,\$trigger\_slope,\$offset\_samples,\$num\_of\_meas"

num of meas: manual

Sampling Rate: 4MHz - Record Length (Number of Samples): manual -

GO

GO

GO


## Implemented DECT test cases

Transmitter test cases:


- Accuracy and stability of RF carriers
- Measurement of packet timing jitter
- Transmission burst and transmitted power
- RF carrier modulation parts 1-4
- · Emissions due to modulation
- Emissions due to transmitter transients
- Spurious emissions when allocated a transmit channel


Receiver test cases:

- Radio receiver sensitivity
- Radio receiver interference performance
- Radio receiver blocking
- Radio receiver intermodulation performance
- Spurious emissions when not allocated a transmit channel



# Accuracy & Stability of RF Carriers: test setup





# Accuracy & Stability of RF Carriers: results


- Verdict criteria:
  frequency offset between ± 50 kHz
- Results all within the limits

Temp (°C)	Volt (V)	Channel	Average Freq offset (kHz)	Compliance with standard	
-12	2.6	5	-25.34	passed	
-12	2.6	0	-25.62	passed	
-12	2.6	9	-25.36	passed	
-12	3.0	5	-25.56	passed	
-12	3.0	0	-25.91	passed	
-12	3.0	9	-25.60	passed	
-12	2.2	5	-25.80	passed	
-12	2.2	0	-26.06	passed	
-12	2.2	9	-25.77	passed	
25	2.6	5	-23.96	passed	
25	2.6	0	-23.88	passed	
25	2.6	9	-23.66	passed	
25	3.0	5	-23.84	passed	
25	3.0	0	-23.86	passed	
25	3.0	9	-23.64	passed	
25	2.2	5	-23.50	passed	
25	2.2	0	-23.72	passed	
25	2.2	9	-23.36	passed	
65	2.6	5	-23.00	passed	
65	2.6	0	-23.10	passed	
65	2.6	9	-22.83	passed	
65	3.0	5	-23.01	passed	
65	3.0	0	-23.13	passed	
65	3.0	9	-22.84	passed	
65	2.2	5	-22.88	passed	
65	2.2	0	-23.00	passed	
65	2.2	9	-22.66	passed	

#### Receiver Interference: test setup

- Signal generator 1 generates desired RF DECT signal on channel M with PRBS sequence in B-field and power level of -73 dBm.
- Signal generator 2 generates a DECT-like interferer signal on channel Y with the corresponding level.

Interferer on RF channel Y	Interferer signal strength (dBm)
Y = M	-84
$Y = M \pm 1$	-60
$Y = M \pm 2$	-39
Y = any other DECT channel	-33



# Receiver Interference Performance: Measurement method

No Is the interferer signal put on all neighbor channels? Yes The interferer power levels recorded should be larger

than the limits in the standard.


Signal generator 1 generates desired RF DECT signal on channel M with power level of -73 dBm

Signal generator 2 generates a DECT-like interferer signal on channel Y with the corresponding level

Combine two signals at RF splitter and feed into the EUT.

EUT sends the received and demodulated data stream to signal generator 1.

A series of successive BER measurements to find maximum interferer level which leads to a BER of 0.001



#### Receiver Interference Performance: results

#### Verdict criteria:

Interferer on RF channel Y	Interferer signal strength (dBm)
Y = M	-84
$Y = M \pm 1$	-60
$Y = M \pm 2$	-39
Y = any other DECT channel	-33

• Results all within the limits

Temp (°C)	Voltage (V)	Channel	Interferer Channel	Interferer level (dBm)	Compliance with standard
25	2.6	0	-3	-21.4	passed
25	2.6	0	-2	-25.5	passed
25	2.6	0	-1	-50.2	passed
25	2.6	0	0	-80.7	passed
25	2.6	0	1	-51.7	passed
25	2.6	0	2	-25.8	passed
25	2.6	0	3	-22.1	passed
25	2.6	0	4	-20.9	passed
25	2.6	0	5	-20.2	passed
25	2.6	0	6	-19.7	passed
25	2.6	0	7	-20.5	passed
25	2.6	0	8	-15.8	passed
25	2.6	0	9	-15.1	passed
25	2.6	0	10	-14.1	passed
25	2.6	0	11	-14.4	passed
25	2.6	0	12	-20.8	passed
25	2.6	5	-3	-18.3	passed
25	2.6	5	-2	-18.2	passed
25	2.6	5	-1	-18.6	passed
25	2.6	5	0	-19.3	passed
25	2.6	5	1	-19.4	passed
25	2.6	5	2	-21.5	passed
25	2.6	5	3	-25.3	passed
25	2.6	5	4	-50.2	passed
25	2.6	5	5	-80.9	passed
25	2.6	5	6	-51.6	passed
25	2.6	5	7	-25.9	passed
25	2.6	5	8	-22.4	passed
25	2.6	5	9	-21	passed
25	2.6	5	10	-20.4	passed
25	2.6	5	11	-20	passed
25	2.6	5	12	-20.8	passed
25	2.6	9	-3	-13.2	passed
25	2.6	9	-2	-18.1	passed
25	2.6	9	-1	-18.2	passed
25	2.6	9	0	-19.4	passed
25	2.6	9	1	-18.4	passed
25	2.6	9	2	-18.2	passed
25	2.6	9	3	-18.9	passed
25	2.6	9	4	-19.4	passed
25	2.6	9	5	-19.7	passed
25	2.6	9	6	-21.5	passed
25	2.6	9	7	-25.4	passed
25	2.6	9	8	-50.1	passed
25	2.6	9	9	-80.4	passed
25	2.6	9	10	-51	passed
25	2.6	9	11	-26	passed
25	2.6	9	12	-22.6	passed

# Advantages of the developed automated system

- Flexibility: extend it to be used for WDCT
- Ease of use
- Documentation

#### Drawbacks

Timing: time to transfer data to PC